

Tabla ASCII

Versión 1.0. Por E. Lavia. GPL

OCT	HEX	DEC	CAR	OCT	HEX	DEC	CAR	OCT	HEX	DEC	CAR
0	00	0	NUL	55	2D	45	-	132	5A	90	Z
1	01	1	SOH	56	2E	46	.	133	5B	91	[
2	02	2	STX	57	2F	47	/	134	5C	92	\
3	03	3	ETX	60	30	48	0	135	5D	93]
4	04	4	EOT	61	31	49	1	136	5E	94	^
5	05	5	ENQ	62	32	50	2	137	5F	95	-
6	06	6	ACK	63	33	51	3	140	60	96	,
7	07	7	BEL	64	34	52	4	141	61	97	a
10	08	8	BS	65	35	53	5	142	62	98	b
11	09	9	TAB	66	36	54	6	143	63	99	c
12	0A	10	LF	67	37	55	7	144	64	100	d
13	0B	11	VT	70	38	56	8	145	65	101	e
14	0C	12	FF	71	39	57	9	146	66	102	f
15	0D	13	CR	72	3A	58	:	147	67	103	g
16	0E	14	SO	73	3B	59	;	150	68	104	h
17	0F	15	SI	74	3C	60	<	151	69	105	i
20	10	16	DLE	75	3D	61	=	152	6A	106	j
21	11	17	DC1	76	3E	62	>	153	6B	107	k
22	12	18	DC2	77	3F	63	?	154	6C	108	l
23	13	19	DC3	100	40	64	@	155	6D	109	m
24	14	20	DC4	101	41	65	A	156	6E	110	n
25	15	21	NAK	102	42	66	B	157	6F	111	o
26	16	22	SYN	103	43	67	C	160	70	112	p
27	17	23	ETB	104	44	68	D	161	71	113	q
30	18	24	CAN	105	45	69	E	162	72	114	r
31	19	25	EM	106	46	70	F	163	73	115	s
32	1A	26	SUB	107	47	71	G	164	74	116	t
33	1B	27	ESC	110	48	72	H	165	75	117	u
34	1C	28	FS	111	49	73	I	166	76	118	v
35	1D	29	GS	112	4A	74	J	167	77	119	w
36	1E	30	RS	113	4B	75	K	170	78	120	x
37	1F	31	US	114	4C	76	L	171	79	121	y
40	20	32		115	4D	77	M	172	7A	122	z
41	21	33	!	116	4E	78	N	173	7B	123	{
42	22	34	"	117	4F	79	O	174	7C	124	
43	23	35	#	120	50	80	P	175	7D	125	}
44	24	36	\$	121	51	81	Q	176	7E	126	~
45	25	37	%	122	52	82	R	177	7F	127	DEL
46	26	38	&	123	53	83	S				
47	27	39	'	124	54	84	T				
50	28	40	(125	55	85	U				
51	29	41)	126	56	86	V				
52	2A	42	*	127	57	87	W				
53	2B	43	+	130	58	88	X				
54	2C	44	,	131	59	89	Y				

NUL	NUL	VT	Vertical Tab	SYN	SYNchronous idle
SOH	Start Of Heading	FF	new page From Feed	ETB	End of Transmission Block
STX	Start of TeXt	CR	Carriage Return	CAN	CANcel
ETX	End of TeXt	SO	Shift Out	EM	End of Medium
EOT	End Of Transmission	SI	Shift In	SUB	SUBstitute
ENQ	ENquiry	DLE	Data Link Escape	ESC	ESCape
ACK	ACKnowledge	DC1	Device Control 1	FS	File Separator
BEL	BEL	DC2	Device Control 2	GS	Group Separator
BS	BackSpace	DC3	Device Control 3	RS	Record Separator
TAB	horizontal TAB	DC4	Device Control 4	US	Unit Separator
LF	new Line Feed	NAK	Negative AcKnowledge		